

NILE TREASURE


(5 REELS 10/20 LINES VIDEO XVGA SLOT GAME)

A style new edition of SUBSINO Video 5-reels and 10/20 lines slot game - Vertical-Monitor 16:9 formats. Players will love the mystical world of ancient Egypt, which features beautiful graphics and a unique bonus that can pay off handsomely.



HOW TO PLAY

- Insert coin(s) or bill(s).
- Press [Play] button to increase bet value on each active line. Or, press [Max Play] button to bet 'Max Bet' and start automatically.
- Then press [Start] button to spin the reels. Press [Stop1], [Stop2], [Stop3], [Stop4] or [Stop5] button to stop the reel or [Start] button again to stop all reels.
- When you have any win combination, you win. Press [Take Score] button to take winning score into Credit, or press [Double Up], [Half Double] or [Re-Double] button to play Double Up game. If Double-Up function is disabled, the system will take scores automatically.
- Press [Help] button to check the result of last game and relative game information. Or, select Denomination value when the function is available.



DOUBLE-UP

GAME FEATURES

- PHARAOH SYMBOL: PHARAOH is wild as joker to replace any symbols, except Red Diamond and Magic Coin symbol.
- SPIN BONUS: Stare one Red Diamond symbol land the middle reel (third reel) and force the coffin to open. There are 6 steps to open the cover of coffin, one Red Diamond may force by random access with 1-5 steps.


It's a serious award with Red Jackpot, Blue Jackpot, Max 500 times of Play or Max. Free Play 30 times. In which, if Pharaoh (Wild) Symbol finds in Free Play, one Pharaoh Symbol will change and convert to 3 Pharaoh Symbols on same reel. And, extra "Free Play +2" symbols find suddenly.

- TREASURE BONUS: Land three Magic Coin symbols on the "Reel_1", "Reel_3" and "Reel_5" trigger the Bonus. It's time for serious fun.

There are two doors on both sides of the way, and choose one for the reward. Continuously choose and ends black smoke find.



SPIN BONUS



FREE PLAY



TREASURE BONUS


INSTALLATION

1) MAIN PCB

- Make sure you have powered-off game.
- Mount 'Game PC Board' on the cabinet.
- Connect 36pin and 10 pin edge connector of the cabinet to male Edge connectors (36pin & 10 pin) of 'Game PC Board'. Refer Page 11 for the diagram of Connector.


2) MONITOR

- Make sure the monitor (CRT/LCD) supports 1366x768 resolutions.
- Connect monitor connector to the monitor socket (VGA D-Sub) of 'Game PC Board'.



3) SPEAKER

- Audio Amplifier of hardware is newest powerful stereo Amplifier. It uses 2 set separate speakers for Audio Out. Connect two speakers to (R+:R-) and (L+:L-) of J3.
- Don't connect any of "Audio Out" to Ground (GND) or link directly the speaker to Ground. In the case of wrong Ground linkage, it will cause PC Board (hardware) damage.
- The 20watt, 8 ohm speaker and more is recommended. If the power of speaker doesn't enough, the "distortion" may find when audio out.




4) TOUCH PANEL

- It's optional and shows relative function automatically after connect.
- Make sure (a) The panel is 3M Microtouch panel or compatible. (b) Connect to DP3 – Touch Panel port. (c) Touch Screen function in Game Setup B of Test/ Setup set to "Enable" to activate. (d) Power Off and On again to ensure the setup is available. The screen will show relative buttons and function this moment.
- Calibrate: Press [Test/ Setup] on the cabinet to go to "Test/ Setup Mode" and select "Touch Screen Calibrate". Touch a Cross symbol for two times to calibrate.

5) BILL ACCEPTOR (SERIAL TYPE)

- The game is available to use both pulse and serial type of Bill Acceptor.
- If use serial type of Bill Acceptor as JCM WBA/ UBA or compatible, adjust Dip Switch Dip#1 to ON and link the connector of Bill Acceptor to DP2 – Bill Acceptor.

6) CONTROL PANEL



Establish above buttons on the panel. Refer the page of Connector Diagram.

- ▶ STOP1, STOP 2, STOP 3, STOP 4, STOP 5
Stop the reel by [Stop1], [Stop2], [Stop3], [Stop4] and [Stop5].
- ▶ DOUBLE UP, RE-DOUBLE, HALF DOUBLE, LEFT, RIGHT
Select Double-Up Game & Mode by [Double Up], [Half D-UP] (Half Double) or [Re-Double], and Play by [Left] or [Right].
- ▶ START/ALL STOP: Begin the game and again to stop all reels.
- ▶ PLAY: To bet one credit for each lines.
- ▶ TAKE SCORE: Take winning score into Credit.
- ▶ HELP: Check last game and game features before the player bets.

7) POWER ON AND CHECK

- After you do all of above, please power on the game. Check +5V DC on main PCB side. The voltage between +4.95 to 5.05V DC is good.
- Press [Test/ Setup] on the cabinet to go to “Test/ Setup Mode”.
- Refer Page 4 to 7 of “Test/ Setup Mode” to set each setting.
- Also, check each function and movement in Test/ Setup Mode. (All buttons & lamps, TV size and color adjustment ... etc.)
- Please refer to page 11 of “Error” or “Troubleshooting” if you have any problems or malfunctions.



TEST AND SETUP

If you need to check the condition of the game circuitry, controls or set system value, you can use the Test/ Setup Mode. Power ON and Press [Test/ Setup] key will go to the mode, as right.

- Moving the bar by pressing [Stop1] button. After choosing one of the contents with the bar, press [Stop5] to enter.
- Press [Start] to exit and back to game mode of main screen. In the case, the value you adjusted would available instantly, which don't necessary to turn off the power.

1) SCREEN TEST

- Use this screen to check the color of monitor and the size of pictures.
- The color bands in the center should be Red, Green, Blue and White from left to right.
- The Cross Hatch test pattern has a white grid on a black background. The check as follows:
 - ▶ The grid line should be straight, and the lines should not have excessive pincushion or barrel distortion.
 - ▶ “Out” line of grid line is same size as “Out” line of game screen, which should able to be seen without overflow of grid lines on screen.
- If the screen does not match above description, adjust the monitor as described in the monitor’s manual.
- Press [Start] button to back main menu.



2) SWITCH AND BUTTONS TEST

Use this screen to check the buttons and switch in this game.

- To check the functioning of each button and switch, activate it and watch the corresponding “OFF” letters change to “ON”. If the “ON” and “OFF” letters don’t appear correctly, check the hardness connections and switches.
- Press [Start] button to back main menu.



3) OUTPUT TEST

Use this screen to check the lamp of buttons in this game.

- To check the functioning of each output, including Counters and lamp of button. Press [Stop1] to move and press [Stop5] to test as watch corresponding lamp ON.
- Counters, Bill Inhibit, Coin Inhibit and HP Full Out are to test the action, no lamp.
- Press [Start] button to exit.



4) SOUND TEST AND VOLUME SETUP

Use this screen to check all game sounds and setup the volume as soft volume control.

- Adjust the volume by pressing [Stop1] to decrease and [Stop2] to increase.
- Choose a sound by pressing [Stop3] button (previous) or [Stop4] button (next), and the machine will make a sound in the moment.
- Press [Start] button to back main menu.



5) GAME SETUP A

The setup items are important and operated by important person as owner only. The password is necessary before enter the screen of Game Setup A. The default value is 111111 (six 1) and enable to change in same password screen.

[Stop1] button for 1; [Stop2] button for 2; [Stop3] button for 3;
[Stop4] button for 4; [Stop5] button for 5;

When the password input with correct, “OK!” is shown on the screen. To change new password, press [Max Bet] button and input new password as you want. Or, press [Start] button to enter ‘Game Setup A’. Use the screen to manually adjust the game setting.



- Moving the bar by pressing [Stop1] button. Select the setting value by pressing [Stop5] button.
- Press [Start] button to back main menu. In the case, the value you adjusted would available instantly, which don't necessary to turn off the power.

CONTENTS	SETTING SELECTION (Underline item is default)
COIN	1, 2, 5, <u>10</u> , 20, 25, 50, 75, 100, 200, 300, 500, 1000, Disable
KEYIN	1, 2, 5, 10, 20, 25, 50, 75, <u>100</u> , 200, 300, 500, 1000, Disable
PAYOUT	1, 2, 5, <u>10</u> , 20, 25, 50, 75, 100, 200, 300, 500, 1000, Disable
KEYOUT	1, 2, 5, 10, 20, 25, 50, 75, <u>100</u> , 200, 300, 500, 1000, Disable
BILL IN	1, 2, 5, <u>10</u> , 20, 25, 50, 75, 100, 200, 300, 500, 1000, Disable
MIN. PLAY	10, 20, 40, 60, 80, 100
MAX. PLAY	100, 200, 300, 400, <u>500</u>
WIN RATE	90, 91, 92, 93, 94, <u>95</u> , 96, 97, 98
GAME LIMIT	5000, 10000, 20000, 30000, 40000, <u>50000</u> , 60000, 80000, 100000, 150000, 200000, 300000, 500000
WIN RATE WAVE	<u>NORMAL</u> , HIGH
DOUBLE FUNCTION	<u>ENABLE</u> , DISABLE
RE-DOUBLE	<u>ENABLE</u> , DISABLE
HALF-DOUBLE	<u>ENABLE</u> , DISABLE
DOUBLE RATE	91, 92, 93, 94, 95, 96, <u>97</u> , 98
DOUBLE LIMIT	5000, 10000, 20000, <u>30000</u> , 40000, 50000, 60000, 80000, 100000
MIN. JP BET	<u>10</u> , 20, 30, 40, 50, 60, 70, 80, 90, 100

TICKET OUT	1, 2, 5, <u>10</u> , 20, 25, 50, 75, 100, 200, 300, 500
TICKET OUT MODE	MAX. 1 TK, MAX. 2 TK, MAX. 3 TK, MAX. 4 TK, MAX. 5 TK, <u>NO LIMIT</u>
TICKET CONTROL	<u>TICKET OUT</u> , INTERFACE, ATTENDANT

- a. Coin: Adjust how many credits per insert coin. To close Coin function set to “Disable”.
- b. Keyin: Adjust how many credits per Keyin. To close Keyin function set to “Disable”.
- c. Payout: Adjust how many credits per pay coin. To close Payout function set to “Disable”.
- d. Keyout: Adjust how many credits per pay Step when Keyout. To close Keyout function set to “Disable”.
- e. Bill In: Adjust how many credits per Bill signal.
- f. Min Bet: Adjust how many min bets to start the game.
- g. Max Bet: Adjust how many max bets can bet at one play.
- h. Win Rate: Adjust total rate % of game.

The win Rate is calculated and defines as follows:

$$\text{Win Rate} = \text{Total Won Score} / \text{Total Played Score}$$

Since this is quite different from some games, which defined the rate as “Coin Out” divided by “Coin In” (Usually call Payout Rate). You shouldn't set the win rate at the same value used in the games. In our experience, the ideal Win Rate is 94%.

Please don't RESET except necessary. To stabilize the rates, the game should operate a period (more long, more steady) for the balance as setup.

- i. Game Limit: Adjust how many credits game can hold.
- j. Win Rate Wave: It's to assign the prizes and rate. Big wave has more big prizes and focus more win or lose. Small wave has more small prizes and rate with more steady.
- k. Double Func.: Play D-Up game when Main Game won. The play score in D-Up is winning score in main game.
- l. Re-Double: The play score in Double Up is twice winning score in main game.
- m. Half Double: The play score in Double Up is a half of winning score in main game.
- n. Double Rate: The rate of D-Up game and defines as Win Rate.
- o. Double Limit: To limit the winning score in Double Up. The system will take the score automatically when winning score is over Double Limit.
- p. Min. Jackpot Bet: Min Bet to win the Jackpot.
- q. Ticket Out: Adjust how many credits per Ticket
- r. Ticket Out Mode: It limits Max. Tickets out.
- s. Ticket Control: To drive Ticket Dispenser by Subsino PC board (Direct) or additional Sub-Board (Interface) or by Attendant.

6) GAME SETUP B (NO PASSWORD)

The setup items are general ones and can operate by the staff in field. The password is unnecessary for the function of Game Setup B. Use the screen to manually adjust the game setting.

CONTENTS	SETTING SELECTION (Underline item is default)
TOUCH SCREEN	ENABLE, <u>DISABLE</u>
DEMO MUSIC	<u>ENABLE</u> , DISABLE
DEMO SHOW	<u>ENABLE</u> , DISABLE
KEYOUT TYPE	<u>ZERO</u> , REST
MAX. PAY TOKENS	200, 300, <u>400</u> , 500, 1000, FREE
BILL INHIBITION	<u>N.C.</u> , N.O.
HOPPER SW TYPE	<u>N.C.</u> , N.O.
SKILL STOP	ENABLE, <u>DISABLE</u>
LINE	<u>10</u> , 20
BILL ACCEPTOR	<u>JCM</u> , ICT, MEI

- Touch Screen: To enable or disable Touch Function.
- Demo Music: To enable or disable demo music.
- Demo Show: To enable or disable demo function.
- Keyout Type: Adjust Keyout should take to 0 (zero) or under one Keyout value (rest).
- Max Pay Tokens: Adjust max coins are paid, which to avoid the hopper empty.
- Bill Inhibition: For Bill Acceptor. N.C. - Normal close (low), N.O. – Normal Open (Hi).
- Hopper Sw. Type: For Hopper. N.C. - Normal close (low), N.O. – Normal Open (Hi).
- Skill Stop: To enable or disable the mode of Skill Stop. If set to enable, five reels will spin continuously until push Stop1, Stop2, Stop3, Stop4 or Stop5 button to stop the reel.
- Line: Set how many active lines for playing.
- Bill Acceptor: For serial port of Bill Acceptor.

7) TOUCH SCREEN CALIBRATE

The item appears only when Touch Panel was connected. It's to calibrate the touch position. Enter the item and touch a Cross symbol for two times to calibrate.

8) DIP SWITCH FUNCTION

Except Screen Setup, some of functions are defined and setup from Dip Switch of PC Board, as follows:

DIP SWITCH		1	2	3	4	5	6	7	8
DOOR OPEN	N.C. N.O.		ON OFF						
HOPPER PULSE (Milli-Second)	30 ms 40 ms 50 ms 60 ms			OFF ON OFF ON	OFF OFF ON ON				

BOOK

Press [Book] button to enter Book screens. Press [Stop5] to enter next page and [Stop1] button for previous page. Press [Start] button to back normal game.

First Page



CURRENT RECORD	
COIN	
PAY OUT	
KEY IN	
KEY OUT	
BILL IN	
NET	
TOTAL TIMES	
TOTAL PLAYED	
TOTAL WON	

The page shows the records from last “check out”.

Total Times: Total played times.

Total Played: Total played score.

Total Won: Total won score.

“Check Out”: To clear this page. Please refer Page 9, Reset function for Clear Current Record Only.

Second Page



SCORE		COUNTER	
COIN			
PAY OUT			
KEY IN			
KEY OUT			
BILL IN			
NET			
TOTAL			
MAIN			
DOUBLE			

The Score column of top form shows the score of Coin, Payout, Keyin, Keyout, Bill In and Net.

The Counter column shows "System Counters". It didn't able to clear by anyway and affected by Reset function, which to compare relatively with machine's mechanical counters when “check out each time”.

(Total/ Main/ Double) Played & Won

Played scores and Won scores in Total/ Main game/ Double game.

(Total/Double) Play Times & Win Times

Played times & Win times in Total/Double game.

Power Times: The times of Power ON.

Third Page



TIMES		SCORE	
SPIN BONUS			
TREASURE BONUS			
FREE PLAY			
TOTAL			
MAIN			
DOUBLE			

The page shows win times and score of Bonus.

(Spin Bonus/ Treasure Bonus/ Free Play) Times

Win times of Spin Bonus, Treasure Bonus & Free Play.

(Spin Bonus/ Treasure Bonus/ Free Play) Score

Win score of Spin Bonus, Treasure Bonus & Free Play.

Fourth & Fifth



Both pages show win times of each prize.

Sixth Page



The page shows last 10 played records. (Press [Stop2] to move the record and [Stop3] to View the record)

RESET (Clear)

● **CLEAR ALL**

Turn off the power of machine. Turn on [Book] and [Setup] Key simultaneously and then turn on the power of machine. (If [Book] or [Setup] make by the buttons, you should press without release.)






The screen will show “System Reset”, which means all of Book data have cleared and game setup values have changed to default value. ("System Counters" in the second page of Book remain unchanged and cleared to zero.).

- ▶ RESET button on the board is unavailable in current version.
- ▶ You should do RESET if you change the Master Rom (Rom_1) or after changed the Win Rate.

● **CLEAR CURRENT RECORD ONLY (CHECK OUT)**

Turn on [Book] Key (or press [Book] button) to enter first page of Book for Current Record. Press [Stop2] and [Stop3] button simultaneously to clear the data of this page. The total records (second page) for from initial operation remain unchanged by this function.

MACHINE LAYOUT



General Style

Deltronic

Please check the JP1 and JP2 on board for the Ticket Dispenser.

ERROR MESSAGE

MESSAGE	DESCRIPTION
System Error	The system may a little confusion instantly. Please do Reset function.
Coin Jam	Power off. Remove the jammed coin from coin selector and power on again. For general error (without jam), press directly “Reset Error” button.
Hopper Jam	Power off. Remove the jammed coin from the hopper and power on again. For general error (without jam), press directly “Reset Error” button.
Hopper Empty	Hopper without Coins/Tokens. Please power OFF and insert Coins/Tokens then power ON again.

TROUBLESHOOTING

SITUATION	FIX
Coin Error	Check coin switch, coin selector and wire wrong.
No sound	<ul style="list-style-type: none"> ● Check the wire of (R+:R-) and (L+:L-) of J3. Two Speaker GND need to be wired separately and don't use same ground. ● Check “Volume setup” on setup page whether close or not.
The counter doesn't work	Check the +12V DC (or +5V DC) line of the counter wire. The wires sometimes are not linked together 10 pin edge connector side of hardness. Please re-wire.
Malfunction of the button, switch and lamps	Check the GND wire. The button, Switch GND has to wire with common GND. Or, check micro switch of button is too old or dirty and the lamp whether out of order.
Coin or Keyin with wrong value	<ul style="list-style-type: none"> ● Check Coin and Keyin wire. Keyin SW port may wire to Coin SW or Bill Acceptor and so on. Please re-wire to correct port. ● Check Game Setup.
Test/ Setup unavailable	Check connection of GND wire between “Test/ Setup” line and common GND line. The GND wire needs to connect with other common GND line.
The Monitor unregulated or Wavy	Adjust the brightness, size and so on as described in the monitor's manual.
Touch Screen doesn't react	<ul style="list-style-type: none"> ● Make sure the panel is 3M Microtouch panel or compatible, and connect to DP3 – Touch Panel port. ● Check “Game Setup B” of Test/ Setup Mode”, Touch Screen set to “Enable” item. And then, power Off and On again to ensure the setup is available.

CONNECTOR DIAGRAM

NILE TREASURES (USA)


COMPONENT SIDE A	36 PIN	SOLDER SIDE B
	1	
	2	
	3	
	4	
	5	
	6	
Ticket Out button	7	
Ticket SW	8	
Start	9	
Help/ Stop3	10	
Play/ Stop5	11	
Take Score/ Stop1	12	
Stop4	13	
Attendant	14	
Reset Error	15	
Stop2	16	
	17	
Coin	18	Keyin
Door Alarm	19	
Book	20	Test/ Setup SW
Payout	21	Keyout SW
	22	Hopper Coin SW ⁽¹⁾
Coin Meter	23	Attendant Lamp
Keyin Meter	24	
	25	
Bill Meter	26	
Payout Meter	27	
Keyout/ Ticket Meter	28	
Start Lamp	29	
Stop3 Lamp	30	
Play/ Stop5 Lamp	31	
Take Score/ Stop1 Lamp	32	
Stop4 Lamp	33	
Stop2 Lamp	34	Coin GND
	35	
GND	36	GND

COMPONENT SIDE A	10 PIN	SOLDER SIDE B
GND	1	GND
GND	2	GND
+5V	3	+5V
+5V	4	+5V
+12V	5	+12V
	6	
⁽²⁾ Hopper Control	7	HP VCC ⁽³⁾
	8	
GND	9	GND
GND	10	GND

⁽¹⁾ Hopper Coin SW: Out signal for Hopper

⁽²⁾ Hopper Control: In signal for Hopper

⁽³⁾ HP VCC - (DC+12V)



- Clear Error button: To correct instantly the message of “Coin Error”, “Coin Jam” and “Hopper Jam” etc after fix.